

MAC 4100

AM-FM STEREO RECEIVER

McIntosh
The Compendium



FRONT PANEL: Anodized aluminum panel. Meters: TUNING and SIGNAL STRENGTH. LED POWER LEVEL columns in 10dB increments from 0.1W to 100W and POWER GUARD lights. Illuminated tuning dial. Indicator lights: AUX 1, AUX 2, AM, FM, PH 1, PH 2. AFL light. FM MPX light. Tuning control. 7 TAPE 2: IN and OUT jacks. INPUT SELECTOR: AUX 1, AUX 2, AM, FM, PH 1, PH 2. Push switches: MONITOR TAPE 1 and TAPE 2, TAPE COPY T1®T2 and T2®T1, MONO, FM MUTE, SPEAKERS 1, 2 and 3. POWER: ON or off. EQUALIZER FREQUENCY controls: 30, 150, 500, 1500 and 10k. LOUDNESS: FLAT to MAX. BALANCE. VOLUME. HEADPHONES jacks 1 and 2. Handles.



BACK PANEL: AC outlets: 2 SWITCHED, 1 UNSWITCHED. Power cord. MAIN FUSE. ⌋ TURNTABLE section: 2 UNSWITCHED AC outlets (TURNTABLE auto-on), switch: AUTO or MANUAL, FUSE. ⌋ Built-in ferrite loopstick. ANTENNA section: push terminals for external AM, GROUND, 300 Ω FM. 75 Ω FM ANTenna coax input. ⌋ Left and Right output push terminals: SPEAKER 1, 2 and 3. ⌋ Left and Right JUMPERS: POWER AMP IN and PREAMP OUT. RECORDER: TAPE 1 IN and OUT, TAPE 2 IN and OUT. ⌋ SCOPE outputs: TP 1 (VERTICAL) and TP 2 (HORIZONTAL). GROUND binding post. INPUTS: PH 1, PH 2, AUX 1, AUX 2.

AM SECTION: Sensitivity: 75uV IHF. S/N: 45dB IHF. Distortion: 1%. Response: 3500Hz @ -6dB. Adjacent Channel Selectivity: 30dB IHF. Image Rejection: 65dB.

FM SECTION: Sensitivity: 2uV (11.2 dBf) IHF. S/N: 70dB IHF. Distortion: 0.38% in Stereo. Response: 20-15kHz (+0 -1dB). Capture Ratio: 1.8dB. Selectivity: 75dB IHF. Spurious Rejection: 90dB IHF. Image Rejection: 80dB IHF. Stereo Separation: 45dB. SCA Rejection: 60dB.

MAC 4100

AM-FM STEREO RECEIVER

McIntosh

The Compendium

SPECIFICATIONS: 100w/channel into 4 ohms, 75w/channel into 8 ohms.

Response: 20-20kHz (+0 -0.5dB). **Distortion:** .05%. **Noise and Hum:** power amp -95dB, aux -90dB, phono -80dB. **Damping Factor:** 30 or greater. **Input Impedance:** power amp 22k, aux 100k, phono 47k and 87pF. **Input Sensitivity:** power amp 2.5V, aux 0.25V, phono 2.0mV. **Program Equalizer:** 30, 150, 500, 1500 and 10,000Hz boost or cut 12dB. **Sentry Monitor.** **Direct coupled.** **Power Guard.** **Power Requirements:** 120V at ??? Watts.



MAC 4100 - Sold from June 1978 - September 1985. S/N: BY1001~BY2899 & BY3001~DL1137

Size: 5-1/4"H, 17-9/16"W and 13-1/2"D. **Weight:** 42 lb. **\$1,999.00**